

FIELD-PROVEN COTS, MOTS AND CUSTOM MILITARY POWER SOLUTIONS

M3916 SERIES AC/DC POWER SUPPLY



PRODUCT HIGHLIGHTS

- AC/DC POWER SUPPLY
- SINGLE PHASE INPUT (50/60/400Hz)
- CE MARKING (IEC 62368-1)
- HIGH POWER FACTOR
- HIGH DENSITY
- SINGLE DC OUTPUT
- UP TO 500 W









Cham, Switzerland
www.enercon-europe.com
sales@enercon-europe.com
+41 41 740 4554

Global Headquarters

Netanya, Israel
www.enercon.co.il
sales@enercon.co.il
+972-73-246 9200



Gurgaon, India www.mpsindia.in sales@mpsindia.in +91-124-651 0010

Applications

Military (Airborne, ground-fix, shipboard), Ruggedized, Telecom, Industrial

Special Features

- Miniature size
- High efficiency
- Wide input range
- High power factor
- Input / Output isolation
- Inrush Current Limiter
- External Inhibit (On/Off)
- Fixed switching frequency
- Externally synchronize
- EMI filters included
- Remote sense compensation
- Indefinite short circuit protection with autorecovery
- Over-voltage shutdown with auto-recovery
- Over temperature shutdown with auto-recovery

Electrical Specifications

AC Input

Option 1:

85 to $265\,V_{AC}$; 50/60Hz Single-phase, $10A_{max}$ IAW MIL-STD-1399-300B Type I

(115 V_{rms} / 60 Hz)

Option 2:

103 to 127 V_{AC}; 400Hz Single-phase, 10A _{max}

Isolation

Input to Output: 1000 V_{DC} Input to Case: 1000 V_{DC} Output to case: 200 V_{DC}

Efficiency

115 V_{rms} / 400 Hz ≥ 80% 230 V_{rms} / 50 Hz ≥ 85% (24 V_{DC} output, full load, 25°C)

DC Output

Voltage range: 24 to 50 V_{DC} Current range: 0 to 20 A Power range: 0 to 500 W

 $3.3 \le V_{DC} < 24V$ output voltages: Consult factory for details

Line/Load regulation

Less than 1% (no load to full load, -40 °C to +85 °C)

Turn on Transient

Output voltage overshoot during power on < 5%

Load Transient Response

Output load change from 50% -100% -50%, output dynamic response < 5%.

Ripple and Noise

 $100 - 150 \, mV_{p-p}$, typical (max 1%) without external capacitance.

Date: June 14, 2021 Rev b Page **2** of **13**

Electromagnetic Compatibility

EMC (MIL-STD)

Designed to meet * MIL-STD-461F:

Conducted Emission	CE101, CE102	
Conducted Susceptibility	CS101, CS114, CS115, CS116	
Radiated Emission	RE101, RE102	
Radiated Susceptibility	RS101, RS103	

EMC (EN/IEC)

Radiated Emission	EN55032 CLASS A
Conducted Emission	EN33032 CEA33 A
Harmonic current Emission	IEC6100-3-2 CLASS A
Voltage Fluctuation & Flicker	IEC6100-3-3

Immunity Test (EN/IEC)

Test Type	Test Method Test Type/Level/C	
ESD	EN61000-4-2	Enclosure; Contact; ±4Kv; [B]
Radiated Immunity	EN61000-4-3	(80-6000) MHz; 10V/m; [A]
EFT	EN61000-4-4	±2kV; [B]
Surgo	EN61000-4-5	L-L: ±1kV; [B]
Surge		L-E: ±2kV; [B]
Conducted Immunity	EN61000-4-6	150kHz – 80MHz ; 10Vrms; [A]
Magnetic Field	EN61000-4-8	50Hz; 30A/m; [A]
Voltage dips and short interruptions	EN61000-4-11	50Hz; (100/60/30)%; [B & C]

^{*}Compliance achieved with shielded harness and static resistive load. Depending on actual configuration, may require an external filter (M4916).

Date: June 14, 2021 Rev b Page **3** of **13**

Protections *

Input

- Inrush Current Limiter
 Initial input current surge to charge internal capacitances is limited internally.
- Under Voltage Lock-Out
 Unit protects itself (no damage) below 80 V_{AC} @ full load.

Output

- Active Over Voltage Protection 10% ± 2% above nominal voltage.
- Passive Over Voltage Protection
 Transorb at output selected 20%
 ± 5% above nominal voltage.
- Over Load / Short Circuit
 10 30% above maximum
 current, indefinitely (Hiccup).

General

Over Temperature Protection
 Shutdown at base plate temp.
 above +105°C ± 5°C Automatic recovery at base plate temp.
 below +95°C ± 5°C

Environmental Conditions

Designed to Meet MIL-STD-810F

Temperature

Methods 501.4 & 502.4

Operating: -40°C to +85°C (at baseplate)
Storage: -55°C to +125°C (ambient)

Altitude

Method 500.4

Procedures I – Storage/Air transport: up to 70,000 ft. (non-operational) Procedure II – Operation/Air Carriage:

up to 40,000 ft. (operational)

Humidity Method 507.4

Up to 95% RH

Vibration

MIL-STD 810F, Method 514.5, Procedure I, Category 24, General minimum integrity exposure, IAW Figure 514.5C-17, 1 hour per axis

Shock

Method 516.5 Procedure I

Functional shock,40g, 15-23ms, Terminal peak

Sawtooth shock pulse

Salt Fog

Method 509.4

Reliability

150,000 hours, calculated IAW MIL-HDBK-217F Notice 2 at +85°C baseplate, Ground fixed conditions.

Environmental Stress Screening (ESS)

100% of delivered power supplies are tested at low ambient temperature, high baseplate temperature and at standard room temperature.

Additional tests, such as random vibration and thermal cycling can be added. Consult factory for details.

^{*}Thresholds and protections can be modified / removed – please consult factory

Pin Assignment

J1 - Input connector


Type: Positronic CBM3W3M81000/AA or eq.

Mates with:

Shell: Positronic CBM3W3S00000/AA or eq.

Pins: FS4820D/AA-15 or eq.

Pin No.	Function	
A1	NEUTRAL	•
A2	PHASE	•
А3	CHASSIS	•



J2 - Output connector

Connector type: M24308/23-39F or eq. **Mates with:** M24308/4-3F or eq.

Pin No.	Function		
1	SIGNAL RTN		•
2	SYNC		0
3	SENSE	+	③
4	VOUT	+	•
5	VOUT	+	•
6	VOUT	+	•
7	VOUT	+	•
8	VOUT	+	•
9	VOUT RTN	_	•
1 0	VOUT RTN	_	•

Pin No.	Function		
11	VOUT RTN	-	•
12	VOUT RTN	ı	•
13	VOUT RTN	I	•
14	INHIBIT		•
15	SENSE RTN	l	②
16	VOUT	+	•
17	VOUT	+	•
18	VOUT	+	•
19	VOUT	+	•
20	VOUT		•

Pin			
No.	Function		
21	VOUT RTN	_	•
22	VOUT RTN	-	•
23	VOUT RTN	-	•
24	VOUT RTN	ı	•
25	VOUT RTN	ı	•



Date: June 14, 2021 Rev b Page **5** of **13**

Functions and Signals

SENSE

The SENSE line is used to achieve accurate voltage regulation at load terminals. To use this feature, connect this pin directly to load's positive terminal.

If this function is not required, short SENSE pin to OUTPUT pins as close as possible to the unit.

SENSE RTN

The SENSE RTN line is used to achieve accurate voltage regulation at load terminals. To use this feature, connect this pin directly to load's negative terminal.

If this function is not required, short SENSE RTN pin to OUTPUT RTN pins as close as possible to the unit.

<u>Note</u>: The use of remote sense has a limit of voltage dropout between the converter's output and the load's terminals of approximately ±1V of nominal output voltage.

INHIBIT

The INHIBIT signal is used to turn the power supply ON and OFF.

OPEN – Power supply active (output turned on).

SHORT to Signal RTN – Power supply inhibited (output turned off). If this

function is not required, leave this pin unconnected.

Optional to change the logic of these signals. Please consult with the factory.

SYNC

The SYNC signal is used to synchronize the power supply's switching frequency to system's clock. Valid external clock frequency is square wave, $500kHz \pm 25kHz$, $V_{p-p} = 0V - 5V$.

If this function is not required, leave this pin unconnected - the power supply will use its internal clock.


SIGNAL RTN

Both INHIBIT and SYNC signals are referenced to this pin. This pin is floating from both input and output.

CHASSIS


The CHASSIS pin allows additional connection of unit's chassis to system ground.

Typical Connection Diagram




Date: June 14, 2021 Rev b Page **6** of **13**


Optional Connection Diagram with external EMI Filter




Outline Drawing



Date: June 14, 2021 Rev b Page **7** of **13**




Date: June 14, 2021 Rev b Page **8** of **13**






Date: June 14, 2021 Rev b Page **10** of **13**

5:



Date: June 14, 2021 Rev b Page **11** of **13**



DETAIL B

NOTES:

- I. CONNECTORS:
 - I.I: JI INPUT CONNECTOR CBM3W3M81000 OR EQ. I.2: J2 OUTPUT CONNECTOR HDC25S50000-I5 OR EQ.
- 2. HEAT DISSIPATION AREA 25,590 mm^2
- 3. WORKMANSHIP SHALL BE MIL-STD-454, REQT. 9
- 4. MATERIAL: ALUMINUM 6061-T651& AL 5052-H32
- 5. FINISH: CHEMICAL CONVERSION COAT PER MIL-DTL-5541, TYPE II, CLASS IA.
- 6. ENGRAVING:
 - CHARACTERS: HEIGHT 3mm, WIDTH 0.6mm, DEPTH 0.4mm.
 - ENGRAVING FILLED WITH BLACK COLOR.

Notes

- 1. Dimensions are in inches [mm]
- 2. Tolerance is: $. \texttt{X} \pm 0.3 \text{ in} \\ . \texttt{XX} \pm 0.15 \text{ in}$
- 3. Weight: 1.4 kg, Typical

Standard Configurations

Part number	Input		Output	
Part number	Voltage range	Frequency	Voltage	Current
M3916-803	1-phase, 85 to 265 V _{AC}	50 / 60 / 400 Hz	$24V_{DC}$	20 A
M3916-804	1-phase, 85 to 265 V _{AC}	50 / 60 / 400 Hz	28 V _{DC}	18 A
M3916-805	1-phase, 85 to 265 V _{AC}	50 / 60 / 400 Hz	48 V _{DC}	10.5 A

- •These configurations are REACH Compliant.
- •The aluminum parts are chromate conversion coated per MIL-DTL-5541F, Type II CLASS 1A or eq.

Additional standard configurations available. Consult factory for details.

Note: Specifications are subject to change without prior notice by the manufacturer.

Date: June 14, 2021 Rev b Page **13** of **13**